



Online store WWW.LYNXGEAR.LV
Company: SIA LATLYNX
info@lynxgear.lv, +371 26159668
Reg. No. 45403038162, VAT Reg. No.
LV45403038162,
Legal address: Baznicas iela 8,
Aizkraukle, Aizkraukles novads,
LV-5101, LATVIJA
Bank Account: LV87UNLA0050021387494
AS SEB Bank, SWIFT: UNLALV2X

ORDER CONFIRMATION

Not Rated Yet



Sales price 79,95 €

Salesprice with discount

Incl. VAT 21%: 13,88 €



Description

- Receives FM and DAB+ for news
- bluetooth function
- works with rechargeable battery, hand crank, batteries (3x AAA) or solar
- bright flashlight with 3 different light modes
- power bank, reading lamp
- headphone jack, hanging loop, alarm clock, memory up to 40 stations
- SOS alarm button
- compact and robust

The compact and robust crank radio is ready to function anytime and anywhere. It receives messages via FM, DAB+ and has the option of being connected via Bluetooth. The radio has an integrated and rechargeable lithium battery that can be charged via USB Type-C, the integrated crank generator or, in an emergency, via the integrated solar cell in sunshine. In addition, the emergency radio can also be operated with standard AAA batteries. Equipped with power bank (4000mAh), flashlight and reading lamp, alarm clock, date and time display, memory for up to 40 transmitters, headphone jack, SOS alarm button and hanging loop. The powerful flashlight can be used with three different light modes. The SOS alarm button triggers



Online store WWW.LYNXGEAR.LV
Company: SIA LATLYNX
info@lynxgear.lv, +371 26159668
Reg. No. 45403038162, VAT Reg. No.
LV45403038162,
Legal address: Baznīcas iela 8,
Aizkraukle, Aizkraukles novads,
LV-5101, LATVIJA
Bank Account: LV87UNLA0050021387494
AS SEB Bank, SWIFT: UNLALV2X

ORDER CONFIRMATION

a loud alarm to draw attention in an emergency. Ideal for camping and outdoor activities.

- 15,3 x 5,3 x 7,5 cm
- Material ABS plastic
- Output standard USB 5V / 1.7A
- Input USB-C DC 5V / 2A
- Lithium-ion battery 21700 / 3.7V
- Solar panel 0.45 W 33 mA
- Headphone output for 3.5 mm
- SOS button
- Bluetooth
- Power bank function for approx. 1 to 2 cell phone charges
- LED reading lamp 250 lumens, 2 W
- LED flashlight 400 lumens, 1.5 W
- Operating hours:
 - Radio (FM/DAB+) approx. 12 hours
 - LED reading lamp approx. 42 hours
 - LED flashlight approx. 72 hours
- Charging time by hand crank 15 minutes for approx. 5 minutes of radio
- including USB-C cable and wrist strap
- the AAA batteries are not included in the scope of delivery

Brand country - Germany.